arXiv:1210.3872v1 [cs.NI] 15 Oct 2012

Traffic-Aware Relay Sleep Control to Improve Energy Efficiency in Joint Macro-Relay Networks

Na Deng, *Student Member, IEEE*, Ming Zhao, *Member, IEEE*, Sihai Zhang, *Member, IEEE*,
and Wuyang Zhou, *Member, IEEE*

***Abstract*—In this letter, we consider a joint macro-relay network with densely deployed relay stations (RSs) and dynamically varied traffic load measured by the number of users. An energy-efficient strategy is proposed by intelligently adjusting the RS working modes (active or sleeping) according to the traffic variation. Explicit expressions related to the network energy efficiency are derived based on stochastic geometry theory. Simulation results demonstrate that the derived analytic results are reasonable and the proposed strategy can significantly improve the network energy efficiency.**

***Index Terms*—Energy efficiency, relay sleep, macro-relay networks, stochastic geometry, traffic-aware.**

I. INTRODUCTION

The coexistence of relays and conventional macrocells namely joint macro-relay network is proposed as a promising network deployment to provide coverage extension and throughput enhancement, while significantly lowering the network energy consumption [1]. Nevertheless, the existing network planning and operation still has great space to be improved on energy efficiency (EE) if the traffic load fluctuation is considered. The traditional cellular networks, especially densely deployed ones, are mostly designed to keep the transmit power always on in order to provide cell coverage and quality of service (QoS) guarantee ignoring the traffic dynamics. As a result, during low traffic periods such as nights or holidays, or in some sparse spots, many relay stations (RSs) are underutilized but still active, which leads to substantial circuit power consumption [2]. Therefore, if we can trace the traffic variation and intelligently adjust the RS working modes (active or sleeping), a great amount of energy could be saved, which is the focus of our work.

Early studies on energy efficient sleep control mainly focus on base stations (BSs). For relays, only [3] investigates the joint RS placement and RS sleep behavior to minimize the total power consumption of a one-dimensional cellular network. Unlike the previous works, in this letter, we consider a joint macro-relay network with densely deployed RSs and dynamically varied traffic load. An efficient RS energy saving strategy is proposed by switching some RSs into sleeping mode when the traffic load is lower than a predefined threshold. Different from BS sleeping, it is unnecessary to cooperate with neighboring BSs and consider their load conditions before each RS makes its mode switching decision, because the resident user equipments (UEs) in the coverage of the sleeping RSs are still served by the original BS rather than the neighboring BSs. Thus, switching off the RSs just turns the cooperative UEs (CO-UEs, served by RSs) into non-cooperative UEs (NC-UEs, served by BSs). Furthermore, instead of relying on system-level simulations only, we establish an analytical model based on the two-scale approximation proposed in [4] for evaluating the energy savings brought from the proposed strategy using stochastic geometry theory. By such a two-scale approximation, the coverage area of a RS can only be within a unique Voronoi-cell [5] of a BS, i.e., the UE covered by a RS is also in the coverage of the corresponding macro-BS, which guarantees the radio coverage and service quality after mode switching. Subsequently, explicit expressions related to the network EE are derived. To the best of our knowledge, there is no literature discussing about traffic-aware RS sleep control and presenting the corresponding theoretical analysis on network EE. In addition, the comparison between the RSs being always active and the RSs with intelligent mode switching is carried out to demonstrate the EE gain of the proposed strategy.

II. NETWORK MODEL

Consider the downlink of a joint macro-relay network, where BSs and RSs are modeled as two homogeneous Poisson point processes (HPPPs) Φ_b, Φ_r with density λ_b, λ_r, respectively. Each RS has a circular coverage with radius R. The CO-UEs are distributed according to a HPPP with density λ_{in} in each circular area, and the NC-UEs are distributed in the whole network according to another HPPP with density λ_{out}. All the HPPPs are mutually independent. The two-scale approximation in [4] is adopted, where a CO-UE can only be covered by a unique RS, and the coverage area of a RS can only be within a unique Voronoi-cell of a BS.

We assume that each NC-UE (or RS) is served by its closest base station and each CO-UE is served through the RS covering it. The BS-to-RS link is modeled as a microwave link, which can suppress interference and simplify the subchannel allocation. The transmit power is P_B for all BSs and P_R for all RSs. For simplicity, we adopt a standard pathloss propagation model with pathloss exponent $\alpha > 2$. Regarding fading, we assume that all links experience Rayleigh fading with parameter μ (denoted by h for signal link and $g_.$ for interference links). For all receivers the noise power is σ^2.

The authors are with the Department of Electronic Engineering and Information Science (EEIS), University of Science and Technology of China (USTC), Hefei, PRC, 230026 (e-mail:ndeng@mail.ustc.edu.cn, {zhaoming, shzhang, wyzhou}@ustc.edu.cn).

This work was supported by National programs for High Technology Research and Development (SS2012AA011702), NSFC (61172088), and partially supported by CMCC T-Ring Project 2011.

A. Proposed RS Sleeping Strategy

Each RS has two working modes, i.e., active and sleeping. Which mode a RS should be in depends on the current traffic load measured by the number of UEs in the RS's coverage (denoted by U_{in}, $U_{in} \sim Poisson(\lambda_{in}\pi R^2)$). If U_{in} exceeds the predefined threshold U_{th}, the RS will be activated. Otherwise, the RS will be turned to sleeping mode and its serving BS will serve the UEs in its coverage. Note that U_{th} is a key factor affecting the network EE in the proposed strategy, and how to value it to achieve the optimal EE of a given network is investigated in Section IV. The probability of RS working in the active mode is obtained as

$$\begin{aligned} P_{on} &= Pr(U_{in} > U_{th}) = 1 - \sum_{i=0}^{U_{th}} \frac{(\lambda_{in}\pi R^2)^i}{i!} e^{-\lambda_{in}\pi R^2} \\ &= 1 - \frac{1}{U_{th}!}\Gamma(U_{th}+1, \lambda_{in}\pi R^2) \end{aligned} \tag{1}$$

Then the active and sleeping RS density can be represented by $\lambda_{r_o} = \lambda_r P_{on}$ and $\lambda_{r_s} = \lambda_r(1-P_{on})$, respectively.

B. Distribution of UEs

Let U_c be the number of CO-UEs covered by an active RSs, and its distribution is

$$P\{U_c = i\} = P\{U_{in} = i | U_{in} > U_{th}\} = \begin{cases} 0, & i \le U_{th} \\ \frac{P\{U_{in}=i\}}{P_{on}}, & i > U_{th} \end{cases} \tag{2}$$

For the number of NC-UEs denoted as U_{nc}, its distribution can not be straightforwardly obtained due to the proposed RS sleeping strategy, because the current NC-UEs consist of two parts, one is the UEs only covered by BSs, and the other is the UEs covered by the sleeping RSs. Let U_{nc}^{out} and U_{nc}^{in} denote the numbers of these two types of NC-UEs, respectively. The probability generating function (PGF) of U_{nc}^{out} is given by equation (2) in [4]:

$$G_{U_{nc}^{out}}(z) = \frac{343}{8}\sqrt{\frac{7}{2}}\left(\frac{7}{2} - \frac{\lambda_{out}}{\lambda_b}(z-1)\right)^{-\frac{7}{2}} \tag{3}$$

and the distribution of U_{nc}^{in} and the corresponding PGF are as follows,

$$P\{U_{nc}^{in} = i\} = P\{U_{in} = i | U_{in} \le U_{th}\} = \begin{cases} \frac{P\{U_{in}=i\}}{1-P_{on}}, & i \le U_{th} \\ 0, & i > U_{th} \end{cases} \tag{4}$$

$$\begin{aligned} G_{U_{nc}^{in}}(z) &= \frac{1}{P\{U_{in} \le U_{th}\}} \sum_{i=0}^{U_{th}} \frac{(\lambda_{in}\pi R^2)^i}{i!} e^{-\lambda_{in}\pi R^2} z^i \\ &= \frac{e^{-\lambda_{in}\pi R^2(1-z)}}{(1-P_{on})U_{th}!}\Gamma(U_{th}+1, \lambda_{in}\pi R^2 z) \end{aligned} \tag{5}$$

The number of UEs covered by each sleeping RS is independent and identically distributed (i.i.d.) with the same PGF, which is also independent of the distribution of U_{nc}^{out}. Using the two theorems of PGF, i.e., the sum of independent random variables and the sum of a random number of i.i.d. random variables, we can obtain the PGF and probability distribution of U_{nc}^{in} as

$$G_{U_{nc}}(z) = G_{U_{nc}^{out}}(z) \cdot G_{r_s}\left(G_{U_{nc}^{in}}(z)\right) \tag{6}$$

$$P\{U_{nc} = i\} = \frac{G_{U_{nc}}^{(i)}(0)}{i!}, i = 0, 1, ... \tag{7}$$

where $G_{r_s}(z) = \frac{343}{8}\sqrt{\frac{7}{2}}\left(\frac{7}{2} - \frac{\lambda_{r_s}}{\lambda_b}(z-1)\right)^{-\frac{7}{2}}$.

C. Spectrum Allocation and Usage

The available spectrum for a cell is evenly divided into M subchannels. We assume that RSs are given a separate frequency band from BSs for no cross-tier interference. Thus a partition (M_b, M_r) is made, where M_b and M_r are the available subchannels for BS transmissions and RS transmissions, respectively. Each BS (or RS) allocates its subchannels randomly and independently of other BSs (or RSs). We assume that each UE needs one subchannel for accessing the network, and when the number of UEs is larger than the number of currently available subchannels, they are served by time-sharing with equal time proportion. Thus, the probability that a subchannel is used by a BS (or RS) is

$$P_{busy,b} = \frac{1}{M_b}\sum_{i=0}^{\infty} \min(i, M_b)\mathrm{P}\{U_{nc} = i\} \tag{8}$$

$$P_{busy,r} = \frac{1}{M_r}\sum_{i=U_{th}+1}^{\infty} \min(i, M_r)\mathrm{P}\{U_c = i\} \tag{9}$$

III. ANALYSIS OF NETWORK ENERGY EFFICIENCY

In this section, we analyze the network EE of the proposed RS sleeping strategy. The energy efficiency in this paper is defined as the ratio of spectral efficiency to power consumption with unit bps/Hz/W. Here we use the mean achievable rate to measure the spectral efficiency. Since the cellular network is homogeneous according to our model, the EE of the whole network is equivalent to that of an arbitrary Voronoi-cell. We first derive the mean achievable rates of both CO-UEs and NC-UEs in a cell and then present the expression of network EE. In order to make the theoretical expressions more concise and tractable, we set $\alpha = 4$.

A. Non-Cooperative UEs

The UE is served by occupying one of the subchannels available for the BS at a distance r with the transmit power $P_b = P_B/M_b$. The received signal-to-interference-and-noise ratio (SINR) experienced by the UE is given by $\gamma_1 = \frac{P_b h r^{-\alpha}}{I_b + \sigma^2}$, where $I_b = \Sigma_{i \in \Phi_b' \backslash b_0} P_b g_i R_i^{-\alpha}$ is the interference from the BSs occupying the same subchannel as the UE (excluding the serving BS itself which is denoted by b_0), and $R_.$ is the distance between the UE and an interfering transmitter. Then the coverage probability denoted as $P_{c_1}(T_u)$ is given by equation (14) in [4]:

$$\begin{aligned} &P_{c_1}(T_u) = Pr(\gamma_1 > T_u) \\ &= \pi\lambda_b\sqrt{\frac{\pi P_b}{\mu T_u \sigma^2}}\exp\left(\frac{\kappa^2(T_u)P_b}{4\mu T_u\sigma^2}\right) Q\left(\kappa(T_u)\sqrt{\frac{P_b}{2\mu T_u \sigma^2}}\right) \end{aligned} \tag{10}$$

where T_u denotes the target SINR of UEs, $Q(x) = \frac{1}{\sqrt{2\pi}}\int_x^{\infty} e^{-y^2/2}dy$, and $\kappa(T) = \pi\lambda_b(1 + P_{busy,b}\sqrt{T}\arctan\sqrt{T})$. If a UE is out of "coverage", i.e., its received SINR is less than the target SINR, which means the UE fails to decode the message from the transmitter, thus no effective rate will be produced. Therefore, in order to obtain the mean achievable rate, we have to derive the probability distribution of γ_1 conditioned on the UE being in "coverage".

$$Pr(\gamma_1 \le T \,|\, \gamma_1 > T_u) = \begin{cases} 0, & T \le T_u \\ \frac{Pr(\gamma_1 \le T) - Pr(\gamma_1 < T_u)}{P_{c_1}(T_u)}, & T > T_u \end{cases} \quad (11)$$

The conditional probability density fuction (PDF) $f_{\gamma_1}(t|\gamma_1 > T_u)$ can be obtained by differentiating (11) with respect to T. Then the mean achievable rate and the sum rate of NC-UEs in a macro-cell can be derived below.

$$\begin{aligned} \tau_{nc} &= \int_{T_u}^{+\infty} \ln(1+t) f_{\gamma_1}(t|\gamma_1 > T_u) dt \\ &= \int_0^{+\infty} \frac{P_{c_1}(e^t - 1)}{P_{c_1}(T_u)} dt + \int_0^{T_u} \frac{1 - P_{c_1}(t)}{P_{c_1}(T_u)(1+t)} dt \\ &\quad - \ln(1+T_u)\left(\frac{1}{P_{c_1}(T_u)} - 1\right) \end{aligned} \quad (12)$$

$$\tau_{sum}^{nc} = \sum_{i=1}^{+\infty} \min(M_b, i) P\{U_{nc} = i\} \tau_{nc} \quad (13)$$

B. Cooperative UEs

For CO-UEs, we adopt the selection decode-and-forward (SDF) [6] as the transmission scheme without regard to the direct link. In the first phase, BS transmits the message to RS. If the RS decodes the message correctly, it will forward the message to the UE in the second phase, otherwise not. A typical RS is served by its closest BS at a distance r with transmit power P_{br}, and its received signal-to-noise ratio (SNR) is given by $\gamma_2 = \frac{P_{br} h r^{-\alpha}}{\sigma^2}$. The coverage probability of a RS denoted by $P_{c_2}(T_r)$ is expressed as

$$\begin{aligned} P_{c_2}(T_r) &= Pr(\gamma_2 > T_r) \\ &= \pi\lambda_b \sqrt{\frac{\pi P_{br}}{\mu T_r \sigma^2}} \exp\left(\frac{\pi^2 \lambda_b^2 P_{br}}{4\mu T_r \sigma^2}\right) Q\left(\frac{\pi\lambda_b}{\sqrt{\frac{2\mu T_r \sigma^2}{P_{br}}}}\right) \end{aligned} \quad (14)$$

Similarly, the coverage probability and mean achievable rate of the CO-UEs, respectively denoted by $P_{c_3}(T_u)$ and τ_c, are given directly due to the limited space. Thus, the sum rate of CO-UEs in a macro cell is obtained.

$$\begin{aligned} P_{c_3}(T_u) = &\frac{1}{R^2}\sqrt{\frac{\pi P_r}{\mu T_u \sigma^2}} \exp\left(\frac{\pi^4 (\lambda_{r_o}^{''})^2 P_r}{16\mu\sigma^2}\right)\left(Q\left(\pi^2 \lambda_{r_o}^{''}\sqrt{\frac{P_r}{8\mu\sigma^2}}\right)\right. \\ &\left. - Q\left(\pi^2 \lambda_{r_o}^{''}\sqrt{\frac{P_r}{8\mu\sigma^2}} + R^2\sqrt{\frac{2\mu T_u \sigma^2}{P_r}}\right)\right) \end{aligned} \quad (15)$$

where $\lambda_{r_o}^{''} = \lambda_{r_o}^{'} P_{busy,r}$, and $\lambda_{r_o}^{'} = \lambda_{r_o} P_{c_2}(T_r)$.

$$\begin{aligned} \tau_c = \frac{P_{c_2}(T_r)}{2P_{c_3}(T_u)} &\left(\int_0^{+\infty} P_{c_3}(e^t - 1) dt + \int_0^{T_u} \frac{1 - P_{c_3}(t)}{1+t} dt\right. \\ &\left. - \ln(1+T_u)\Big(1 - P_{c_3}(T_u)\Big)\right) \end{aligned} \quad (16)$$

$$\tau_{sum}^{c} = \sum_{i=1}^{+\infty}\sum_{j=1}^{+\infty} iP\{U_{r_o^{'}} = i\} \min(M_r, j) P\{U_c = j\} \tau_c \quad (17)$$

C. Power Model and Energy Efficiency

We use the power consumption model in [7], which has two types, i.e., the pessimistic and optimistic models, depending on the traffic load L. In the optimistic model, L can vary between zero load and full load ($L = 0 - 100\%$), while in the pessimistic model, L is fixed at full load. The optimistic and pessimistic models for both BSs and RSs are respectively given below

$$P^{bo}(L) = 2.42 L P_{RFmax}^{b} + 0.115 P_{RFmax}^{b} + 0.0121 L + 37 \quad (18)$$

$$P^{bp} = 2.85 P_{RFmax}^{b} + 557 \quad (19)$$

$$\begin{aligned} P^{ro}(L) = &\ 2.42 L P_{RFmax}^{r} + 0.115 P_{RFmax}^{r} + 0.0121 L \\ &+ (P_{RFmax}^{r}/P_{RFmax}^{m}) \times 37 \end{aligned} \quad (20)$$

$$P^{rp} = 2.85 P_{RFmax}^{r} + (P_{RFmax}^{r}/P_{RFmax}^{m}) \times 557 \quad (21)$$

where for BS, $L = U_{nc}/M_b$ and for RS, $L = U_c/M_r$. Based on the power model above, we derive the average sum power consumption of both BSs and RSs as

$$\begin{aligned} P_{sum}^{b} = &\sum_{i=0}^{M_b - 1} P^{bo}(L) Pr\{U_{nc} = i\} + P^{bp} \sum_{i=M_b}^{+\infty} Pr\{U_{nc} = i\} \\ &+ \sum_{i=0}^{+\infty} iPr\{U_{r_o} = i\} P_{br} \end{aligned} \quad (22)$$

$$\begin{aligned} P_{sum}^{r} = &\sum_{i=0}^{+\infty} iPr\{U_{r_o^{'}} = i\} \left(\sum_{j=0}^{M_r - 1} P^{ro}(L) Pr\{U_c = i\}\right. \\ &\left. + P^{rp} \sum_{j=M_r}^{+\infty} Pr\{U_c = i\}\right) + \sum_{i=0}^{+\infty} iPr\{U_{\widehat{r_o^{'}}} = i\} P^{ro}(0) \end{aligned} \quad (23)$$

where $U_{\widehat{r_o^{'}}}$ represents the number of the RSs out of "coverage" and its corresponding intensity is denoted as $\widehat{\lambda}_{r_o}^{'} = \lambda_{r_o}(1 - P_{c_2}(T_r))$. Then according to the definition of network EE in [4], we give the EE (denoted as Q) expression as follows

$$Q = \frac{\tau_{sum}^{nc} + \tau_{sum}^{c}}{P_{sum}^{b} + P_{sum}^{r}} \quad (24)$$

TABLE I
SYSTEM PARAMETERS

Symbol	Description	Value
λ_b	density of BSs	$10^{-5}\ BS/m^2$
λ_r	density of RSs	$10^{-4}\ RS/m^2$
P_B/P_R	transmit power	43dBm/38dBm (BS/RS)
M	number of subchannels	100 (M_b=80, M_r=20)
R_r	radius of RS	20m
μ	Rayleigh fading parameters	1 (normalized)
σ^2	noise power	-120dBm
T_u/T_r	SINR threshold of UE/RS	1/1



Fig. 1. EE versus traffic intensities, i.e., λ_{in} and λ_{out}.



Fig. 2. Energy efficiency versus U_{th} with various stations intensities.

IV. SIMULATION RESULTS

In simulations, the EE of a joint macro-relay network with traffic-aware RS sleep control is evaluated. The default configurations of the system model are indicated in Table I.

Fig. 1 compares the EE of two joint macro-relay networks, one with RS mode switching and the other with RS always on, under various traffic intensities reflected by both λ_{in} and λ_{out} for $U_{th} = 3$. The simulation results match the analytical results well, thus corroborating the accuracy of our theoretical analysis. It is observed that as λ_{in} increases, the EE curves with sleep control exhibit a double-convex shape and the optimal value of EE occurs in the early stage, which shows the absolute advantage and effectiveness on EE improvement of the proposed strategy compared with the curves with non-sleep control in the low traffic cases. In addition, the EE goes up with the increasing of λ_{out}, but the shape of the curve is essentially unchanged. The reason should be that the BSs are always on which makes the power consumption constant, then serving more NC-UEs means obtaining higher mean achievable rate, thus the EE is improved.

Fig. 2 depicts how the traffic threshold U_{th} affects the EE with various densities of both BSs and RSs for $\lambda_{out} = 10^{-5}$, $\lambda_{in} = 10^{-2}$. All curves with RS sleep control are convex, where each of them has its own U_{th} corresponding to the optimal EE and a certain range of U_{th} with better EE than that with non-sleep control. Furthermore, the effect of stations densities on EE should not be ignored. Comparing the curve marked by "$\circ$" with that marked by "$\times$", although both of the two curves have almost the same optimal value of EE, the former has better EE for $U_{th} < 9$ while the latter has better EE for $U_{th} > 9$, which is closely related to the number of RSs switched off, the usage of the subchannels in each BS, and the traffic intensities. Meanwhile, the EE of the curve marked by "$\diamond$" is the worst. The reason should be that the stations densities in this case are excess for the current traffic load and large numbers of subchannels keep idle while the power is still consumed due to the stations switched on, which results in the decrease of the EE.

V. CONCLUSIONS

In this letter, we have studied the EE of a joint macro-relay network with densely deployed RSs and dynamically varied traffic load. An energy-efficient strategy is proposed by smartly switching the RS working modes according to the traffic variation to improve the EE during low traffic periods. With the aid of stochastic geometry theory, we analyze the network EE including the mean achievable rates of both NC-UEs and CO-UEs and the network power consumption. Simulation results verify the theoretical analysis, demonstrate the significant EE improvement brought by the proposed strategy and indicate which threshold should be selected in order to maximize the EE and how the traffic intensities and stations densities affect the EE, which are very important for designing green communication networks.

REFERENCES

[1] V. Bhargava and A. Leon-Garcia, "Green cellular networks: A survey, some research issues and challenges," in *Communications (QBSC), 2012 26th Biennial Symposium on*. IEEE, 2012, pp. 1–2.

[2] H. Kim and G. De Veciana, "Leveraging dynamic spare capacity in wireless systems to conserve mobile terminals' energy," *IEEE/ACM Transactions on Networking (TON)*, vol. 18, no. 3, pp. 802–815, 2010.

[3] S. Zhou, A. Goldsmith, and Z. Niu, "On optimal relay placement and sleep control to improve energy efficiency in cellular networks," in *Communications (ICC), 2011 IEEE International Conference on*. IEEE, 2011, pp. 1–6.

[4] N. Deng, S. Zhang, W. Zhou, and J. Zhu, "A stochastic geometry approach to energy efficiency in relay-assisted cellular networks," *accepted by (GLOBECOM 2012), IEEE*. [Online]. Available: http://home.ustc.edu.cn/~ndeng/DENG_Globecom_Relay.pdf

[5] M. Haenggi, J. Andrews, F. Baccelli, O. Dousse, and M. Franceschetti, "Stochastic geometry and random graphs for the analysis and design of wireless networks," *Selected Areas in Communications, IEEE Journal on*, vol. 27, no. 7, pp. 1029–1046, 2009.

[6] J. Laneman, D. Tse, and G. Wornell, "Cooperative diversity in wireless networks: Efficient protocols and outage behavior," *Information Theory, IEEE Transactions on*, vol. 50, no. 12, pp. 3062–3080, 2004.

[7] C. Khirallah, J. Thompson, and H. Rashvand, "Energy and cost impacts of relay and femtocell deployments in long-term-evolution advanced," *Communications, IET*, vol. 5, no. 18, pp. 2617–2628, 2011.